

## VM5808H 8 x 8 HDMI Matrix Switch

### IR Command code

- Carry frequency : 38KHz
- IR Protocol : NEC
- Customer code: 00FF
- Data code :

FUNCTION	DATA CODE
OUTPUT	
PORT 1	1D
PORT 2	19
PORT 3	0C
PORT 4	0E
PORT 5	01
PORT 6	02
PORT 7	03
PORT 8	1A
INPUT	
PORT 1	04
PORT 2	05
PORT 3	06
PORT 4	1E
PORT 5	07
PORT 6	08
PORT 7	09
PORT 8	1B
ON	0F
OFF	12

